# UNCLASSIFIED

# AD 401 135

Reproduced
by the

DEFENSE DOCUMENTATION CENTER

**FOR** 

SCIENTIFIC AND TECHNICAL INFORMATION

CAMERON STATION, ALEXANDRIA, VIRGINIA



UNCLASSIFIED

MOTICE: When government or other drawings, specifications or other data are used for any purpose other than in connection with a definitely related government procurement operation, the U.S. Government thereby incurs no responsibility, nor any obligation whatsoever; and the fact that the Government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data is not to be regarded by implication or otherwise as in any manner licensing the holder or any other person or corporation, or conveying any rights or permission to manufacture, use or sell any patented invention that may in any way be related thereto.

сору 65 ор тш





MARINE PHYSICAL ARCRATORY
of the Scrippe Institution of Oceanography
San Diego 52, California

# DIGITAL ENCODER AND PAPER TAPE PUNCH

EARL D. SQUIER

SPONSORED BY
OFFICE OF NAVAL RESEARCH
CONTRACT NONR 2216 (06)



Reproduction in whole or in part is permitted for any purpose of the U. S. Government

1 FEBRUARY 1963

SIO REFERENCE 63-1

401 135

# UNIVERSITY OF CALIFORNIA, SAN DIEGO MARINE PHYSICAL LABORATORY OF THE SCRIPPS INSTITUTION OF OCEANOGRAPHY SAN DIEGO 52, CALIFORNIA

# DIGITAL ENCODER AND PAPER TAPE PUNCH

EARL D. SQUIER

SPONSORED BY
OFFICE OF NAVAL RESEARCH
CONTRACT NONR 2216 (05)

SIO REFERENCE 63-1

1 FEBRUARY 1963

Reproduction in whole or in part is permitted for any purpose of the U.S. Government

F. N. SPIESS/DIRECTOR
MARINE PHYSICAL LABORATORY

MPL-U-25/62

Squier SIO Reference 63-1

### DIGITAL ENCODER AND PAPER TAPE PUNCH

Earl D. Squier

University of California, San Diego Marine Physical Laboratory of the Scripps Institution of Oceanography San Diego 52, California

#### **ABSTRACT**

An all solid-state digital recording system is described along with an example of its operation. The equipment consists of a 200-channel input scan switch, an analog to digital converter, and a paper tape punch.

Input voltages are encoded into 4-, 8-, or 12-bit words and punched on paper tape as 4-bit characters at rates up to 50 characters per second. Provisions are included for formatting the tape for use in the Bendix G15 computer.

# I. INTRODUCTION

The data recording equipment to be described here was designed with its primary objective, the recording of data from the 32 directional beams of the Marine Physical Laboratory ambient sea noise measuring equipment. The possibility of using the equipment for other and varied recording problems was kept in mind, resulting in a flexible digital recording instrument.

# II. GENERAL DESCRIPTION

The equipment shown in the photograph, Fig. 1, consists of a multiple input scan switch, an analog to digital converter, paper tape punch, and controlling electronics. Solid-state electronics is used throughout.

The equipment consists of 3 major units each housed in a  $22' \times 15' \times 16'$  cabinet. These cabinets have hardware to allow them to be stacked, forming one unit.

The upper unit houses the input scan switch, a Vidar model 240 dc voltage to frequency converter and a Computer Measurements Corporation model 1230A binary counter. The input scan switch allows a series of slowly changing voltages to be scanned in sequence. The analog to digital conversion is performed by the converter and binary counter. The converter produces a frequency proportional to the input voltage. The counter then makes a count of this frequency for a fixed period of time. The count is displayed in binary form by neon indicator lamps and is available for transfer to the storage register and paper tape punch.

The center unit is the main control chassis which is made up of Computer Control Co. SPAC series of digital modules and several special circuits. This unit contains circuits for generating the timing and controlling signals as well as circuits for gating and storage of the binary information prior to transfer to the perforator.

SIO Reference 63-1 Squier




Fig. 1 Paper Tape Punch and Encoder

Squier SIO Reference 63-1

The lower unit houses a Tally model 420 tape perforator and Tally model 1424 transistorized drive package.

The equipment will scan any number of devoltages up to 200, convert them to digital form and punch the digital information on 5-level paper tape. Four of the 5 levels are used to form 4-bit characters, the 5th level bit is entered whenever data is being punched. Words of 1, 2 or 3 characters can be punched for each input voltage measured.

Upon completion of the sampling of a series of input voltages, any one format character can be entered along with a length of tape leader. The equipment can be made to stop automatically after the input scan cycle has been completed, or will repeat the cycle until stopped externally.

The tape punching rate can be varied from a maximum of 50 characters per second to 1.6 per second. The upper limit is below the maximum rating of 60 per second specified for the Tally 420 perforator. The lower limit can be extended by use of an external time base.

The sensitivity and dynamic range can be adjusted to suit individual requirements by the use of the Vidar voltage range, the counting period, and the selection of 1-, 2- or 3-character words. See Sensitivity and Range under section IV.

The instrument can be used for sampling of a single channel voltage supplied directly to the converter. The dynamic voltage range of the equipment is greater with this method of operation because of the limited voltage range of the input scan switch.

# III. SPECIFICATIONS

Scan Switch

Number of gates:

200 maximum.

: 8v when used

Maximum input voltage: 8v when used from a 1K source and with

a 1 meg load. Shown on page

Linearity: Variation in gates

over 8v range:

±20 mv.

Converter

Voltage ranges;

0.1, 1.0, 10, 100 and

1000.

Input impedance:

100K on the 0.1v range. 1 meg on all other

ranges.

NOTE: Scan switch gates normally require the 1 meg load.

Time for change in output frequency:

Linearity:

1 cycle. 0.1%.

Drift: Output: Long term 0.1%.
Frequency proportional to input voltage.
100kc maximum on all voltage ranges.

Binary Counter

Gate times:

10, 20, 40, 80, 100, 200, 400, 800 and

1600 ms.

Read-out:

16 binary bits.

Tape Punching Periods

0.02, 0.04, 0.08, 0.16, 0.32 and 0.64 sec with internal time

base.

Storage Register

12 binary bits.

Format

1-, 2- or 3-character data words of 4 data

bits each.

l-character command word optional at the end of the input

scan cycle.

Power Requirement

115v, 60 cycle, 3

amps.

Equipment Weight

Total -- 243 lbs.

Unit 1 - 87 lbs. Unit 2 - 86 lbs.

Unit 3 - 70 lbs.

SIO Reference 63-1 Squier

### IV. DETAILED DESCRIPTION

#### Control Timing

The simplified block diagram, Fig. 2, shows the functional relationships of the major units of the equipment.




Fig. 2 Simplified Block Diagram

The time base unit generates the basic timing and clocking waveforms.

Proper signals from the time base are supplied to the control generator which inserts the necessary time delays for: scanning of the input voltage levels, storage, scanning of the store, and operation of the perforator. The control generator also synchronizes the start with the internal timing and allows for the format character to be punched at the proper time.

The input scan cycle can be started by either the manual start switch, located on the control chassis panel, or by an external 6 volt positive going pulse applied to the external start jack.


The start control forms the starting waveform and then locks out further start signals until reset.

Fig. 3 illustrates graphically the timing events of a 3-character per word scan.

After the start, the control generator opens the number one gate of the input scan switch and the converter produces a frequency proportional to the supplied voltage. After a 2.5 ms delay the binary counter gate is opened and the output of the converter is counted for a period of time determined by the counter gate, preselected by the operator. The counter holds the count until it is transferred to the store. At this time number two input gate is opened and the store is reset. After a delay of .2 ms the count now in the 16-bit binary counter (number one input voltage level) is transferred to the 12-bit storage register. The counter is then reset 2.5 ms later and a new counting cycle is started while the next input voltage is being measured. The count in the store is transferred sequentially to the punch in 4-bit characters, A, B and C, the 3 characters forming a 12-bit data word. One- or two-character words can also be selected by the punch sequence switch.

The cycle illustrated is then repeated until all input voltage levels have been scanned.

The cycle is stopped automatically at the end of an input scan cycle by the last gate opened by the input scan switch. The operation can also be stopped by the manual stop switch.



# NOTE:

- a n GATE OPEN (INPUT VOLTAGE x)
- b COUNTER RESET . 25 MS FROM a
- COUNTER GATE CLOSES
  COUNTER HOLDS COUNT
- n + 1 GATE OPENS (INPUT VOLTAGE y)
  DELAY . 2 MS RESET STORAGE
- DELAY .2 MS RESET STORAGE DELAY .2 MS SET STORAGE INPUT WORD x NOW IN STORE COUNTER RESET 2,5 MS FROM a'
- yl-y2-y3
- 3 CHARACTER WORD x TRANSFERRED TO PUNCH 3 CHARACTER WORD y TRANSFERRED TO PUNCH

Fig. 3 Repetitive Events During a 3-Character per Word Scan

When the recycle switch is in the ON position, the scan cycle will repeat one time after another once the operation is started.

# Input Scan Switch Characteristics

The input scan switch consists of electronically controlled diode gates. These should be

supplied with signals from a low impedance resistive source. The gates will handle up to 8 volts. The curve shown in Fig. 4 shows the linearity of the gates operated from a 1 K ohm source. A group of 50 gates have been compared and a maximum difference in the output of ±20 mv over the range 0-8 volts was observed.

SIO Reference 63-1 Squier




Fig. 4 Linearity Curve

# Sensitivity and Range

The sensitivity and range of the equipment is determined in the analog to digital converter by the choice of converter voltage range and the binary counter gate time. Further control of the sensitivity and range after conversion is accomplished by the selection of the minimum value bit to be punched and the number of characters per word. A 1-character word has 16 units, a 2-character word has 256 units, and a 3-character word has 40% units.

When the input scan switch is used the diodes impose an upper and lower limit on the input voltage. See Input Scan Switch Characteristics.

The counter gate time is a factor in determining the sensitivity of the equipment. The maximum counter gate time is limited by the conversion period. The conversion period must be at least 10 ms longer than the counter gate time which is the time necessary for circuit operation.

#### Data Conversion Rates

The internal time base generator will allow tape punching periods of .02, .04, .08, .16, .32 and .64 seconds. The conversion period is determined by the punch period and the number of characters per word to be punched.

Punch Period Conversion Period Characters per Word

# Tape Format

The paper tape is punched with the Bendix G 15 digital computer coding. Four of the 5 levels are used to form 4-bit characters in a 1-2-4-8 hexadecimal code. The 5th level is entered whenever data is being punched. Data words of 1, 2 or 3 characters can be punched for each input voltage measured.

The absence of the 5th level indicates command or format characters. A 1-character format word will be punched at the end of the input scan cycle, when the format switch is ON. The format character is coded by the four switches.

The format character will be followed by a length of leader. There are two leader lengths available, either 1.25 inches or 7 inches, selected by a switch.

The words are punched on the tape one after another without spacing except for the leader that follows the formut character.

# External Control

A connector is provided for external control of the start, stop, format and recycle operation. The punch period, conversion period and input scan cycle waveforms are also available at this connection.

The data recording program can be placed under the control of external equipment by the use of this connector. Examples of the external control that might be used are counting of the data conversions, grouping of the data samples, or synchronizing with an external time base. Squier SIO Reference 63-1

EXAMPLE: The proper combination of the various controls will be determined by the conditions of the signals to be recorded. The following is an example of the adjustments for one problem. Reference to the detailed description will help in understanding the example.

A voltage of 0 to 5 volts is to be recorded using 2-character words. (256 units, see Sensitivity and Range.) The 10-volt Vidat range would be used (the overload level would be 8 volts, see Input Scan Switch Characteristics). With the 5-volt input the Vidat would produce a frequency of 50 kc. Using the 10 ms counter gate would allow for a count of 500 (50 kc x 10 ms) with each unit having a value of 10 mv (5V + 500). If counter bits 2 through 9 were transferred to the storage register and punch, the range covered would be 0 to 5.12 volts in 20 mv units.

If the shortest punch period of 20 ms is used, the conversion period would be 40 ms (characters per word times punch period, see *Data Conversion Rates*). This will satisfy the requirement that the conversion period be at least 10 ms longer than the counter gate time.

# V. SINGLE CHANNEL OPERATION

The previous discussion was concerned with the scanning of a number of signal voltages. Another possible mode of operation is the sampling of a single voltage, applied directly to the converter. The sampling is at conversion period rates determined by the control unit time base, either internal or external.

The sampling can be started and stopped by the manual start and stop buttons or by external pulses, refer to *Control Timing*, section IV.

Reference should be made to the Vidar model 240 manual.

### MPL U-DISTRIBUTION

#### DISTRIBUTION LIST

Office of Naval Research
Department of the Navy
Washington 25, D. C.
Attn: Code 466, Copies 1-2
Code 467, Copy 3
Code 468, Copy 4
Code 406T, Copy 5

Commanding Officer
Office of Naval Research
Branch Office
1030 East Green Street
Pasadena 1, California
Copy 6

Commanding Officer
Office of Naval Research
Branch Office
Navy No. 100, Fleet Post Office
New York, New York
Copy 7

Chief, Bureau of Ships
Department of the Navy
Washington 25, D. C.
Attn: Code 335, Copy 8
Code 688, Copy 9
Code 670, Copy 10
Code 370, Copy 11
Code 450, Copy 12

Chief of Naval Operations
Department of the Navy
Washington 25, D. C.
Attn: Op 03EG, Copy 13
Op 03T, Copy 14
Op 32, Copy 15
Op 31, Copy 16
Op 07, Copy 17
Op 07T, Copy 18
Op 71, Copy 19

Chief, Bureau of Naval Weapons Department of the Navy Washington 25, D. C. Attn: Code RU, Copy 20

Commander
Operational Test and Evaluation Force
U. S. Naval Base
Norfolk, Virginia
Copy 21

Commander Submarine Force U. S. Atlantic Fleet Fleet Post Office New York, New York Copy 22

Deputy Commander Submarine Force U. S. Atlantic Force New York, New York Copy 23

Commander Submarine Force U. S. Pacific Fleet Fleet Post Office San Francisco, California Copy 24

Commander Submarine Flotilla ONE Fleet Post Office San Francisco, California Copy 25

Commanding Officer Submarine Development Group TWO Fleet Post Office New York, New York Copy 26

Commander Anti-Submarine Force U. S. Atlantic Fleet U. S. Naval Base Norfolk, Virginia Copy 27

Commander Anti-Submarine Force U. S. Pacific Fleet Fleet Post Office San Francisco, California Copy 28

Commander Destroyer Force U. S. Atlantic Fleet Newport, Rhode Island Copy 29

Commander Key West Test and Evaluation Detachment Key West, Florida Copy 30 Commander Destroyer Development Group TWO Fleet Post Office New York, New York Copy 31

Commander
Destroyer Development Group
U. S. Pacific Fleet
U. S. Naval Shipyard
Long Beach, California
Copy 32

Deputy Commander Pacific
Operational Test and Evaluation
Force
U. S. Naval Air Station, North
Island
San Diego 35, California
Copy 33

U. S. Atlantic Fleet ASW Tactical School Norfolk 11, Virginia Copy 34

Commanding Officer and Director David Taylor Model Basin Washington 7, D. C. Copy 35

Commanding Officer
U. S. Naval Air Development
Center
Johnsville, Pennsylvania
Copy 36

Commanding Officer and Director
U. S. Navy Electronics Laboratory
San Diego 52, California
Copy 37

Commanding Officer and Director
U. S. Navy Engineering
Experiment Station
Annapolis, Maryland
Copy 38

Commanding Officer and Director
U. S. Navy Mine Defense
Laboratory
Panama City, Florida
Copy 39

### **MPL U-DISTRIBUTION**

Commanding Officer and Director
Naval Ordnance Laboratory
White Oak
Silver Spring 19, Maryland
Attn: John Munson, RA Division
Copy 40
S. J. Raff, Copy 41

Systems Analysis Group
Undersea Warfare Research and
Development Council, Room 5224
Naval Ordnance Laboratory
White Oak
Silver Spring 19, Maryland
Copy 42

Commander
U. S. Naval Ordnance Test Station
China Lake, California
Attn: Tech. Library, Code 753
Copy 43

Commander
U. S. Naval Ordnance Test Station
Passadens Annex
3202 East Foothill Boulevard
Passadens 8, California
Attn: Passadens Annex Library
Copy 44

Commanding Officer and Director Naval Research Laboratory Washington 25, D. C. Attn: Code 2000, Copy 45

U. S. Navy Underwater Ordnance Station Newport, Rhode Island Copy 46

Commanding Officer and Director
U. S. Naval Training Device Center
Port Washington, New York
Attn: Tech. Library Division
Copy 47

Commanding Officer and Director
U. S. Navy Underwater
Sound Laboratory
Fort Trumbull
New London, Connecticut
Attn: Code 900, Copy 48
Code 930, Copy 49

Commanding Officer and Director U. S. Navy Underwater Sound Reference Laboratory Box 8337 Orlando, Florida Copy 50

Superintendent
U. S. Naval Postgraduate School
Monterey, California
Attn: Librarian, Copy 51

The Hydrographer
U. S. Navy Hydrographic Office
Washington 25, D. C.
Copy 52

British Naval Staff Washington 25, D. C. Via: NRL, Code 2000 Copies 53-55

Canadian Joint Staff Washington 25, D. C. Via: NRL, Code 2000 Copies 56-57

Director
Armed Services Technical
Information Agency
Arlington Hall Station
Arlington 12, Virginia
Via: ONR 466, Copies 58-67

Supreme Allied Commander

U. S. Atlantic Fleet

ASW Research Center
APO No. 19, New York
Via: (1) ONR Code 466
(2) CNO Op 92C2
(3) Secretariat of
Military Information
Control Committee
Copy 68

Executive Secretary

Committee on Undersea Warfare
National Academy of Sciences
2101 Constitution Avenue
Washington 25, D. C.

Attn: George Woods

Copy 69

Dr. Frederick V. Hunt 222 Lyman Laboratory Harvard University Cambridge 38, Massachusetts Copy 70

Director Hudson Laboratories 145 Palisade Street Dobbs Ferry, New York Copy 71

Director
Ordnance Research Laboratory
Pennsylvania State University
P. O. Box 30
University Park, Pennsylvania
Copy 72

Director
University of Texas
Defense Research Laboratory
P. O. Box 8029
Austin, Texas
Copy 73

Director
Applied Physics Laboratory
University of Washington
1013 East 40th Street
Seattle 5, Washington
Copy 74

Institute for Defense Analysis
Communications Research Division
Von Neuman Hall
Princeton, New Jersey
Copy 75

Director
Woods Hole Oceanographic
Institution
Woods Hole, Massachusetts
Copy 76

University of California, San Diego Scripps Institution of Oceanography La Jolla, California Attn: Director, Copy 77 Library, Copy 78 MPL Campus Office, Copy 79 Spec. Dev., Copy 80 Academic Affairs, Copy 81

1. Signal Processing Techniques	[. Squier, Earl D.	Sponsored by Office of Naval Research Contract Nonr 2216 (05)	UNCLASSIFIED	1. Signal Processing Techniques	I. Squier, Earl D.	Sponsored by Office of Naval Research Contract Nonr 2216 (05) UNCLASSIFIED	
Marine Physical Laboratory Report MPL-U-25/62	DIGITAL ENCODER AND PAPER TAPE PUNCH, by Earl D. Squier, University of California, San Diego, Marine Physical Laboratory of the Scripps Institution of Oceanography, San Diego 52, California. SIO Reference 63-1, I February 1963.	An all solid-state digital recording system is described along with an example of its operation. The equipment consists of a 200-channel input scan switch, an analog to digital converter, and a paper tape punch.  Input voltages are encoded into 4., 8., or 12-bit words and punched on paper tape as 4-bit characters at rates up to 50 characters per second. Provisions	Bendix G15 computer.	Marine Physical Laboratory Report MPL-U-25/62	DIGITAL ENCODER AND PAPER TAPE PUNCH, by Earl D. Squier, University of California, San Diego, Marine Physical Laboratory of the Scripps Institution of Oceanography, San Diego 52, California. SIO Reference 63-1, I February 1963.	An all solid-state digital recording system is described along with an example of its operation. The equipment consists of a 200-channel input scan switch, an analog to digital converter, and a paper tape punch.  Input voltages are encoded into 4-, 8-, or 12-bit words and punched on paper tape as 4-bit characters at rates up to 50 characters per second. Provisions are included for formatting the tape for use in the Bendix G15 computer.	
1. Signal Processing Techniques	I. Squier, Earl D.	Sponsored by Office of Naval Research Contract Nont 2216 (05)	UNCLASSIFIED	l. Signal Processing Techniques	I. Squier, Earl D.	Sponsored by Office of Naval Research Contract Nonr 2216 (05) UNCLASSIFIED	
Marine Physical Laboratory Report MPL-U-25/62	DIGITAL ENCODER AND PAPER TAPE PUNCH, by Earl D. Squier, University of California, San Diego, Marine Physical Laboratory of the Scripps Institution of Oceanography, San Diego 52, California. SIO Reference 63-1, I February 1963.	An all solid-state digital recording system is described along with an example of its operation. The equipment consists of a 200-channel input scan switch, an analog to digital converter, and a paper tape punch.  Input voltages are encoded into 4, 8, or 12-bit words and punched on paper tape as 4-bit characters at rates up to 50 characters per second. Provisions	Bendix G15 computer.	Marine Physical Laboratory Report MPL-U-25/62	DIGITAL ENCODER AND PAPER TAPE PUNCH, by Earl D. Squier, University of California, San Diego, Marine Physical Laboratory of the Scripps Institution of Oceanography, San Diego 52, California. SIO Reference 63-1, I February 1963.	An all solid-state digital recording system is described along with an example of its operation. The equipment consists of a 200-channel input scan switch, an analog to digital converter, and a paper tape punch.  Input voltages are encoded into 4., 8., or 12-bit words and punched on paper tape as 4-bit characters at rates up to 50 characters per second. Provisions are included for formatting the tape for use in the Bendix G15 computer.	